







The module series RSL.... can be used to directly command relays or power contactors up to 230V (manual override) and to signalize "Fault"- and "Run"- messages (e.g. feedback from the power contactor 24V DC / AC). This module provides up to 2 switches, each up to 6 positions.

If you need 7 to 12 positions, there can only be 1 switch (mounted at the lower position). You can order the module with up to 6 Duo-LEDs (red, green or yellow). Their colors can be adjusted by the means of jumper.

RSL model code:

- NOL HIQUEL CODE:

 1. digit: number of LEDs upper position
 2. digit: positions of upper switch
 3. digit: number of LEDs lower position
 4. digit: positions of lower switch

You can adjust the function of the inputs by the means of jumper as well. There you can choose between NC contact and NO contact principle. Yellow and red LEDs cause a collective fault message via the plug-in 5-pole bus system on the collective fault module RSM. There are two group outputs (+24V DC) for creating different priority levels (group 1 = LED 1-3, group 2 = LED 4-6), which are activated by red or yellow coded inputs.

You can trigger a lamp test over the plug-in 5-pole bus system with the RSM... module.

Typeracitizade 3, Ziffer LED's oben 1 des 1 2 des 2 3 des 10d oder grun oder gelo inserted 5 des 1 det urfers	2.8 months pay fact 1.6	\$2 / 26 / 26 24 26 26 26 26 26 26
Normon		15 (2) (3) (4) (4) (4) (4) (4) (4) (4) (4) (4) (4
85.000 85.	61 11 53 12 13 14 19 17 61 11 53 12 13 14 19 17 641 11 53 12 13 14 15 15 663 11 15 15 15 14 15 15 663 11 15 15 15 14 15 15 17 664 11 15 15 15 15 15 15 15 665 11 15 15 15 15 15 15 15 665 11 15 15 15 15 15 15 665 11 15 15 15 15 15 15 665 11 15 15 15 15 15 665 11 15 15 15 15 15 665 11 15 15 15 15 15 665 11 15 15 15 15 15 665 11 15 15 15 15 665 15 15 15 15 665 15 15 15 15 665 15 15 15 15 665 15 15 15 15 665 15 15 15 15 665 15 15 15 665 15 15 15 665 15 15 15 665 15 15 665	Columb
Section 1 26 26 26 26 26 26 26	6: 1115 12 13 14 19 17 6: 1115 12 13 14 14 17 6: 1115 12 13 14 14 15 6: 1115 12 13 14 14 15 7 13 14 14 15 17 7 14 15 15 17 7 15 15 15 15 7 15 15 15 7 15 15 15 7 15 15 7 15 15 7 15 15 7 15 15 7 15	C C C C C C C C C C
Heat Column Col	0+ 11/55	Columb
HELLOW 1	C: 117 2 7 7 1	C C C C C C C C C C

Supply voltage: 24V DC / AC ± 10% Power consumption: max. 60 mA (per LED about 5 mA)

Inputs: Control with 24V DC / AC

Signaling: Duo LEDs, color red, green or yellow

Switches: Switching voltage max. 300V AC / DC Switching current: 150mA Quiescent current: max. 5A Life min. 10,000 operations

Environmental conditions: Operating temperature 0 ... 50 ° C

Transport and storage temperature -20 ... + 70 ° C
Relative humidity 5 ... 95%, non-condensing
Protection class: IP 40, when using transparent coverage up to IP 54

Dimensions: Width 8TE(40.5mm), height 3HE(129mm), for mounting into 19" racks

Installation depth <80 mm Terminals: 2.5mm2 pluggable terminal

CE Conformity
EN 61000-4-2 / IEC 801-2 Electrostatic Discharge ESD
Contact discharge 8 kV / air discharge 8 kV
EN 61000-4-5 / IEC 801-5 Surge
AC supply voltage 4 kV, 0.5 kV DC
Signal lines 2 kV
EN 61000-4-4 / IEC 801-4 Burst
Inputs - Outputs +/- 2 kV
Supply voltage AC / DC +/- 2 kV

subject to technical alternations

copyright, romutec - www.romutec.eu - Jochsbergerstr. 39 - D-91592 Buch am Wald - Tel +49-9867/9790-0

revision date 1. 3. 2017